

Circuit Breakers

Type Q Plug-In Breakers

Selection and Ordering Data

Selection



LOADCENTRES 4



Q115



Q215



Q315



Q1515NC



Q21515CTNC

Full Module (1" per pole) 10,000 A.I.C

Ampere Rating	Catalogue Number	Standard Package
Single Pole		
15 20 25 30 40 50 60 70	Q115 ^③ Q120 ^③ Q125 Q130 Q140 Q150 Q160 Q170	48
Two Pole Common Trip		
15 20 25 30 40 50 60	Q215 Q220 Q225 Q230 Q240 Q250 Q260	24
70 80 90 100 125	Q270 Q280 Q290 Q2100 Q2125	5
150 200	QN2150R ^④ QN2200R ^④	1
Three Pole Common Trip		
15 20 25 30 40 50 60 70	Q315 Q320 Q325 Q330 Q340 Q350 Q360 Q370	3
90 100	Q390 Q3100	2

Half Module (1/2" per pole) 10,000 A.I.C.

Poles	Amps	Catalogue Number ^①	Standard Package
QT Dual (Twin)	15-15	Q1515NC	48
	15-20	Q1520NC	
	15-30	Q1530NC	
	15-40	Q1540NC	
	20-15	Q2015NC	
	20-20	Q2020NC	
	30-15	Q3015NC	
	30-20	Q3020NC	
	30-30	Q3030NC	
	40-15	Q4015NC	

Quad Type (1/2" per pole) 10,000 A.I.C. Common Trip - centre poles only.

Poles	Ampere Rating	Catalogue Number ^②	Standard Package
QT Quad	15-15	Q21515CTNC	24
	15-20	Q21520CTNC	
	15-25	Q21525CTNC	
	15-30	Q21530CTNC	
	15-40	Q21540CTNC	

① Typical catalogue number (ie. Q1515NC) represents two single-pole 15A circuit breakers - total width 1"

② Typical catalogue number (ie. Q21520CTNC) represents two single-pole, outer poles (two 15A 1-pole circuit breakers) and one 2-pole inner breaker with common trip (one 20A 2-pole circuit breaker) - total width 2"

③ Typical CSA Listed for frequent switching applications (SWD). 120V AC Fluorescent Lighting.

④ Requires 4 panel circuits, 2 adjacent and 2 opposite. Two twist outs should be only removed.