

# TORK<sup>®</sup>

## SPECIFICATION SHEET

Project Info:	Type:
Job Ref:	Catalog Number:
Approvals:	Date:

### 400B

#### Indoor Mechanical Plug-In Timers



#### APPLICATIONS

- Automatically turn ON/OFF items in the home.
- Control lamps, radios, televisions, appliances.
- Give the home a "lived in" look while away.
- Save energy and provide security.

#### FEATURES

- **Repeat Schedule:** Daily
- **Variable Timing:** Multiple ON/OFF times.
- **ON/OFF:** Manual ON/TIMER Switch.

403B  
403B2 (2 Pack)



402B



405B

#### ORDERING INFO & CONTACT RATINGS

CAT. NO.	FIG. NO.	UPC CODE	VOLTAGE VAC 50/60Hz	NO. OF OUTLETS	TYPE OF PLUG	DESCRIPTION	VARIABLE TIMING SEGMENTS	RATING			
								RESISTIVE	TUNGSTEN	ELECTRONIC BALLAST (LED)	MOTOR
403B	1	16085	125	1	Polarized	Basic Lighting Timer	30 minute	15A @ 1875W	500W	500VA	1/3HP
402B	2	16091	125	1	Grounded	Heavy Duty 24 hour Timer	30 minute	15A @ 1875W	500W	500VA	1/3HP
405B	3	16094	125	2	Grounded	Two Outlet Automatic Timer	30 minute	15A @ 1875W	500W	500VA	TV-4

NOTE: "▲" = Indicates outlet location.