



**Uphoria Edge LED MR16 (95+ CRI) Series - Dimmer Compatibility List**

Uphoria Edge LED MR16 (95+ CRI) lamps may operate on other dimmers and dimming systems not listed below.

The existence of a dimmer on this list is not a guarantee or warranty of the compatibility of the kit / dimmer combination in all applications.

Actual performance of the products and dimmers may vary.

Transformer		Lightech LET 60				Lightech LET75				Lightech LET105				Lightech LVT-60				HATCH RS12-15M-LED				HATCH** RS12-30M-LED				HATCH PS12-75L5				HATCH** VS12-150WD				B+L technology FX95100			
Brand Name	Model #	1	3	5	8	1	3	5	8	1	3	5	8	1	3	5	8	1	3	5	8	1	3	5	8	1	3	5	8	1	3	5	8	1	3	5	8
Cooper	DLC038	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	N	N	N	N	N	N	N	N	N	Y	Y	Y	Y**	Y**	N	Y	Y	Y	Y	Y
Lutron	MA-600	N	N	N	N	N	N	Y	Y	N	Y	Y	Y	N	Y	Y	N	N	N	N	N	N	N	N	N	N	N	N	Y	N	N	Y	Y	N	Y	Y	Y
Lutron	SCL-153PR	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	N	N	N	N	N	N	N	N	Y	Y	Y	Y	N	Y**	Y	Y	Y	Y	Y	Y
Lutron	MA CL-153-P	N	N	Y!	Y!	N	N	Y*	Y*	Y	Y	Y	Y	N	N	N	N	Y	N	N	N	Y	N	N	N	Y	Y	Y	Y	N	N	Y	Y	Y	Y	Y	Y
Leviton	6674	Y	Y!	Y!	Y!	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	N	N	N	N	N	N	N	N	N	Y	Y	Y	N	Y <sub>(SR)</sub> **	Y <sub>(SR)</sub>	Y <sub>(SR)</sub>	Y <sub>(SR)</sub> **	Y <sub>(SR)</sub> **	Y <sub>(SR)</sub>	Y <sub>(SR)</sub>
Leviton	6673	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N
Leviton	IPL06	Y!	Y!	Y!	Y!	Y!	Y!	Y!	Y!	Y	Y	Y	Y	Y	Y	Y	Y	N	N	N	N	N	N	N	N	Y	Y	Y**	Y**	N	Y**	Y	Y	Y	Y	Y	Y
Leviton	IF3005	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	Y	N	N	N	N	N	N	N	N	Y**	Y	Y	Y	Y	Y	Y
Lutron	CTCL-153P	Y!	Y!	Y!	Y!	Y!	Y!	Y	Y	Y	Y	Y	Y**	N	Y	Y	Y	N	N	N	N	N	N	N	N	Y	Y	Y	Y	N	Y	Y	Y	Y	Y	Y	Y
Lutron	MRF2-6ND	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	N	Y	Y	Y	N	N	N	N	N	N	N	N	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
Lutron	DV CL-153P	Y	Y	Y	Y**	N	N	N	N	Y	Y	Y	Y	N	N	N	N	N	N	N	N	N	N	N	N	Y	Y	Y	Y	N	Y	Y	Y	Y	Y	Y	Y
Lutron	S-600P	N	Y	Y	Y	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	Y	N	N	N	N	N	N	N	N	N	N	Y	N	Y	Y	Y
Lutron	IPE04	Y	Y	Y	Y	Y	Y	Y	Y	N	N	N	N	Y	Y	Y	Y	Y	Y	Y	N	Y <sub>(SR)</sub>	Y <sub>(SR)</sub>	Y**	Y**	N	N	N	N	Y <sub>(SR)</sub>	Y <sub>(SR)</sub>	Y <sub>(SR)</sub>	Y <sub>(SR)</sub>	Y <sub>(SR)</sub> **	Y <sub>(SR)</sub> **	Y <sub>(SR)</sub>	Y <sub>(SR)</sub>
Leviton	IPI06	N	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	N	Y	Y	Y	N	N	N	N	N	N	N	N	N	Y	Y	Y**	N	N	Y <sub>(SR)</sub>	Y <sub>(SR)</sub>	N	Y	Y	Y
Leviton	6615	Y	Y	Y	Y	Y	Y	Y	Y	N	Y	Y	Y	N	N	N	N	N	Y	Y	N	N	Y <sub>(SR)</sub>	Y <sub>(SR)</sub> **	Y <sub>(SR)</sub> **	N	N	N	N	Y	Y	Y <sub>(SR)</sub>	Y <sub>(SR)</sub>	Y	Y	Y	Y
Leviton	6613	N	Y	Y	Y	Y	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	N	Y	Y	N	N	N	N	Y	Y	Y	Y
Lutron	RRD-6NA	Y	Y	Y	Y	N	Y	Y	Y	Y	Y	Y	Y	N	Y	Y	Y	Y	Y	Y	N	Y	Y	Y	Y**	Y	Y	Y	Y	N	Y	Y	Y	Y	Y	Y	Y
Lutron	RRD-10ND	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	N	N	N	Y	N	N	N	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y
Lutron	RRD-6CL	Y	Y	Y	Y	N	Y*	Y	Y	Y	Y	Y	Y	N	Y	Y	Y	N	N	N	N	N	N	N	N	N	N	N	N	N	Y	Y	Y	Y	Y	Y	Y
LE GRAND	H703PTUTCCCV6	N	Y	Y	Y	N	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	N	N	Y	Y	N	N	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y

Y<sub>(SR)</sub> small range

@ on high blink, on low flicker

! flicker on low

\* dimmer needs to be adjusted to low side

\*\* transformer buzz

TRANSFORMERS		LAMP NUMBER							
BRAND NAME	PART #	1	2	3	4	5	6	7	8
LIGHTTECH	LET60	OK	OK	OK	OK	OK	OK	OK	OK
	LET75	OK	OK	OK	OK	OK	OK	OK	OK
	LET105	OK	OK	OK	OK	OK	OK	OK	OK
	LVT60	OK	OK	OK	OK	OK	OK	OK	OK
HATCH	RS12-15M-LED	OK	OK	OK	OK	OK	OK	OK	OK
	RS12-30M-LED	N	N	OK**	OK**	OK**	OK**	OK**	OK**
	PS12-75L5	OK	OK	OK	OK	OK	OK	OK	OK
	VS12-150 **	OK**	OK**	OK**	OK**	OK**	OK**	OK**	OK**
B+L technology	FX95100	OK	OK	OK	OK	OK	OK	OK	OK

\*\* TRANSFORMER BUZZ