

Specification

PROD	UCT NAME :	LED Emergency Light Combo
		(Running Man Sign)
MODE	LNO.:	NX-EMRMCUP
SPECI	FICATION :	AC120-347V; 60Hz; 80mA; 4.5W
WORK	ING TEMP :	-0-40(°C)
CRI(R	۹):	>80
COLO	र:	White Color
LIGHT	SOURCE :	SMD
LIFE T	IME :	50000 hrs
BATTE	RY :	Ni-CD battery (3.6V 1800mAh)
SELF-	POWERED:	120mins
PROD	UCT SIZE :	13.58*2.32*9.05 inch
IP :		Suitable for Damp Locations
APPLI	CATION :	Shop, Hotel etc
WARR	ANTY :	5 years fixture, 2 years battery.
STANE	DARD :	cUL
COLO	R TEMP :	6500K







Feature:

- *Super Bright LED Light Source
- *1.2W per head
- *Nexleds custom patent design heads
- *Combo heads adjustable
- *127-347V universal voltge
- *Two wire design for easy installation
- *Double LED Strip for even light distribution
- *Ni-Cad Battery
- *UL approved 120 mins battery backup time
- *Universal Mounting: Ceiling Mounting, Wall mouting and End mounting;
- *Single/Double side installation
- *Suitable for damp locations
- *Comes with 3pcs pictograms(without arrow, with left arrow and with right arrow)

Product Dimension

Applications:



Suitable for commercial and institutional place: Apartment, hotel, shop, office, school, hospital ...etc.



Warning:

- Review the diagrams thoroughly before beginning.
- •All electrical connections must be in accordance with local codes, ordinances and the National Electrical Code.
- Disconnect power at fuse or circuit breaker before installation or service.
- Do not use outdoors.
- •Do not mount in hazardous locations or near gas or electric heaters.
- Do not let power cords touch hot surfaces.
- •Equipment should be mounted in locations and at certain height where it will not be subject to tampering by unauthorized personnel.
- •The use of accessory equipment is not recommended by the manufacturer
- Do not use this equipment other than intended use.
- •Allow battery to charge for 48 hours before first use.
- •All service should be performed by qualified personnel only.

